



AX400

- | SMALL SIZE, LIGHT WEIGHT.
- | RUGGED CONSTRUCTION.
- | SIMPLE KEY OPERATION.
- | FREQUENCY COVERAGE IS CONTINUOUS FROM 500KHZ - 1300MHZ WITH NO GAPS.
- | MODES OF AM, NFM & WFM AVAILABLE ON ANY FREQUENCY.
- | 400 MEMORY CHANNELS.
- | 10 SEARCH BANKS.
- | 80 SEARCH PASS FREQUENCIES.

Measuring just 97mm(h) x 58mm(w) x 24 mm(d) it is one of the smallest handheld scanner available. For those familiar with other Standard products it is the same case as the C501/601 HT's.

Not only is the AX-400 extremely small but it requires just 2 x AA batteries for internal power and with these fitted still only weight a remarkably light 200 grams.

GENERAL:

Frequency range		500 kHz - 1300 MHz		
Memory channels		400		
Type of memory		EE PROM		
Scanning speed		25 channels / sec		
Sensitivity	10 dB S/N	0.5 - 5 MHz	AM	1.5 μV
		5 - 160 MHz	AM	1.0 μV
	12 dB Sinad	5 - 160 MHz	FM	0.5 μV
			WFM	0.7 μV
			160 - 370 MHz	AM
		160 - 370 MHz	FM	0.7 μV
			WFM	1.0 μV
			370 - 520 MHz	FM
		WFM		1.0 μV
		520 - 1300 MHz	FM	1.0 μV
			WFM	1.0 μV
		Audio output		90 mW
Frequency Step		1kHz, 5kHz, 6.25kHz, 9kHz, 10kHz, 12.5kHz, 15kHz, 20kHz, 25kHz, 30kHz, 50kHz, 100kHz, auto		
Operating Voltage		2.2 - 3.5 V		
Current drain	RX	125 mA		
	Battery save	16 mA		
	Standby	65 mA		
Dimensions (H x W x D) and Weight		98 x 58 x 24 mm, 200 g		
Battery life		20 hours		